# **TECHNICAL DATASHEET**

# Rosenberger

**CLICK CLEANER** 

099 A 0390 CLICK CLEANER 1.25 099 A 0391 CLICK CLEANER 2.5 099 A 0395 CLICK CLEANER RDC

## Description

Handy cleaning device for fiber optic connector tips. It allows cleaning a ferrule endface either through a adapter or directly. A unmating of the connector is not necessary. By pushing the housing, a cleaning tape removes the contamination from the ferrule tip. The nozzle can be extended to reach connectors difficult to access. Three different versions allow cleaning connectors with a ferrule diameter of 1.25 or 2.5 mm.



#### Dimensions

Length ca. 185 mm

#### Weight

ca. 25 g

## Ferrule types

Ø 1.25 mm, PC and APC-typeØ 2.5 mm, PC and APC-type

# Cleaning Cycles

500

| Description                           | Part No    |  |  |
|---------------------------------------|------------|--|--|
|                                       |            |  |  |
| Click Cleaner, for ferrules Ø 1.25 mm | 099 A 0390 |  |  |
| Click Cleaner, for ferrules Ø 2.5 mm  | 099 A 0391 |  |  |
| Click Cleaner, for RDC connectors     | 099 A 0395 |  |  |

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

| Draft      | Date       | Approved       | Date       | Rev. | Engineering change number | Name       | Date       |
|------------|------------|----------------|------------|------|---------------------------|------------|------------|
| S. Schmidt | 2009-12-18 | R. Breitenauer | 2009-08-01 | 002  |                           | S. Schmidt | 2010-04-15 |

Rosenberger OSI GmbH & Co. OHG

Tel.:+49 821 249249-0

www.rosenberger.com/osi; E-Mail: info-osi@rosenberger.com

Page

1 / 1